



#### **MNO**



Online monitoring for oil level in power transformers and reactors.

## Main Features



Signal input in mA or resistive



3 setup levels for contacts actuation (high, low and trip levels)



Analog output for measured level



3 independent output relays (NAF)



Digital output RS485 Modbus RTU or DNP 3 protocols



Contact to fault indication (watchdog)



Power Supply 48 to 265 Vdc/Vac



Maximum and minimum levels

# Quality

Built to comply with strict quality standards and the latest generation of electronic components (SMD). Its hardware was projected to endure several harsh working conditions. It can be mounted directly in the transformer/reactor cabinets in substations, offshore platforms and chemical industries.

It meets requirements levels of supportability and reliability according to the standards IEC, DIN, IEEE and ABNT.

#### Maluminium Enclosure

The aluminium enclosure has a high mechanical resistance and produces a Faraday cage which increases the immunity of the electronic circuit in cases of noise inductions and electric discharges at the equipament.

Easy to install and reduced size: 48 x 96 x 140 mm.



Display with 4 dígits of 13,8 mm height and LED with high luminosity.



Easy configuration through equipment keyboard or via laptop with support of UseEasy software, which emit graphs and reports as well.



Easy handling, with intuitive configuration menus. The pefect set to the user.



To measure the oil level in transformers with expansion tank, its recommended to use a magnetic indicator with resistive output. For some applications it's possible to use the pressure transmitter TPE (Electron).






Proven Quality











### > Technical Data

Power Supply	48 - 265 Vdc/Vac 50/60 Hz
Power Consumption	< 15 W
Operation Temperature	-40 to +85 °C (-40 to +185 °F)
Storage Temperature	-50 to +60 °C (-58 to +140 °F)
Input for Level Measurement	Float (0 to 300 $\Omega$ or 4 to 20 mA)
Measurement Range	0 to 100 %
Analog Outputs	5 configurable outputs with range: 01 / 05 / 010 / 020 / 420 mA
Maximum Error for Input Measurements	0.5% end of scale
Maximum Error for Analog Output	0.5% end of scale
Output Contacts	4 – Potential Free
Maximum Switching Power	70 W / 250 VA
Maximum Switching Tension	250 Vdc / Vac
Maximum Conduction Current	6 A
Communication Protocol	RS485 - Modbus RTU and DNP 3.0 (L2)
Auto Baud Rate	2.400 to 57.600 bps
Frontal Port USB	USB Serial – 2.0
Enclosure DIN IEC 61554	48 x 96 x 140 mm – Aluminium
Fixation	Embedded in Panel Door
Protection Degree (NBR IEC 60529)	IP40 (Front side) ; IP30 (Back side)

# >> Type Tests

- Insulation Voltage (IEC 60255-5): 2kV / 60 Hz / 1 min (to ground);
  Voltage Impulse (IEC 60255-5): 1,2/50 µs / 5 kV / 3 neg e 3 pos / 5 s Interval;
  Electrostatic Discharge (IEC 60255-22-2): Air mode = 8 kV / Contact mode = 6 kV;

- Electrostatic Discharge (IEC 60255-22-2): Air mode = 8 kV / Contact mode = 6 kV;
  Irradiated electromagnetic field immunity (IEC 61000-4-3): 80 A 1000 MHz / 10 V/m;
  Fast electrical transient immunity (IEC 60255-22-4): Power/Input/Output = 4 kV / Serial port 2 kV;
  Surge immunity (IEC 60255-22-5): Phase/Neutral 1 kV, 5 per polar (±) phase-ground/neutral-ground 2 kV, 5 per polar (±);
  Conduced electromagnetic perturbations immunity (IEC 61000-4-6): 0,15 a 80 MHz / 10 V/m;
  Climatic test (IEC 60068-21-14): -40 °C → + 85 °C / 72 hours;
  Vibration resistance (IEC 60255-21-1): 3 axis / 10 150 Hz / 2G / 160 min/axis;
  Vibration response (IEC 60255-21-1): 3 axis / 0,075 mm @ 10 58 Hz / 1G @ 58 150 Hz / 8 min / axis



